

## HDMI Converter-Switcher 5X1



HDC02-M51

The HDC02-M51 Multi-media HDMI Switcher encodes HDMI, DVI, and YPbPr video signals into HDMI output video and audio. The DVI and YPbPr are equipped with different audio formats like Toslink, Coaxial, including right and left inputs and outputs. This device has infrared remote control and lets you switch easily between different types of video and audio formats to the full HDMI digital video and audio display.

### Features:

It has two HDMI inputs, DVI video with toslink, coaxial, or right and left audio inputs, two YpbPr with two toslink, coaxial, or right and left audio inputs

Supports HDMI V1.2a

Supports up to 1080p analog video resolution

Supports 8bit per channel (24bit all channel) deep color.

Supports compressed audio such as DTS Digital, Dolby Digital, DTS-HD, and Dolby True HD.

Supports 165MHz/1.65Gbps per channel (4.95Gbps all channel) bandwidth

Supports toslink, coaxial, or right and left audio inputs for DVI and YPbPr.

Supports HDMI with toslink, coaxial, or right and left audio outputs.

Supports memory function for last viewed selection when turned on again

Supports infrared remote control, RS232, and manual controls for source and audio inputs